



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

REC'D 24 DEC 2003

WIPO

PCT

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

02292728.9

**PRIORITY
DOCUMENT**
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

R C van Dijk

BEST AVAILABLE COPY



Anmeldung Nr:
Application no.: 02292728.9
Demande no:

Anmeldetag:
Date of filing: 31.10.02
Date de dépôt:

Anmelder/Applicant(s)/Demandeur(s):

Motorola Inc.
13 East Algonquin Road
Schaumburg, IL 60196
ETATS-UNIS D'AMERIQUE

Bezeichnung der Erfindung/Title of the invention/Titre de l'invention:
(Falls die Bezeichnung der Erfindung nicht angegeben ist, siehe Beschreibung.
If no title is shown please refer to the description.
Si aucun titre n'est indiqué se référer à la description.)

Communication unit and method of channel estimation in an OFDM communication system

In Anspruch genommene Priorität(en) / Priority(ies) claimed /Priorité(s)
revendiquée(s)

Staat/Tag/Aktenzeichen/State/Date/File no./Pays/Date/Numéro de dépôt:

Internationale Patentklassifikation/International Patent Classification/
Classification internationale des brevets:

H04L7/00

Am Anmeldetag benannte Vertragsstaaten/Contracting states designated at date of
filing/Etats contractants désignées lors du dépôt:

AT BE BG CH CY CZ DE DK EE ES FI FR GB GR IE IT LI LU MC NL PT SE SK TR

COMMUNICATION UNIT AND METHOD OF CHANNEL ESTIMATION IN AN OFDM COMMUNICATION SYSTEM

Field of the Invention

5

This invention relates to an estimation of radio-channel propagation conditions, in order to equalise their effect on transmitted data. The invention is applicable to improving an accuracy of channel estimation in an
10 orthogonal frequency division multiplex (OFDM) wireless receiver.

Background of the Invention

15 Wireless communication systems, for example cellular telephony or private mobile radio communication systems, typically provide for radio telecommunication links to be arranged between a plurality of base transceiver stations (BTSS) and a plurality of subscriber units, often termed
20 mobile stations (MSs).

Wireless communication systems are distinguished over fixed communication systems, such as the public switched telephone network (PSTN), principally in that mobile
25 stations move between BTS (and/or different service providers) and in doing so encounter varying radio propagation environments.

Methods of communicating information simultaneously exist
30 where communication resources in a communication network are shared by a number of users. Such methods are termed multiple access techniques. A number of multiple access techniques exist, such as frequency division multiple

access (FDMA), time division multiple access (TDMA), and code division multiple access (CDMA).

5 The communication link from a BTS to a MS is referred to as the down-link. Conversely, the communication link from a MS to the BTS is referred to as the up-link.

10 In wireless communication systems, there is a need to estimate the effect caused by the 'wireless communication channel' on the data being transmitted. Channel estimation is required so that the received data can be equalised to reduce, restore or minimise signal degradation caused by such transmission channel impairments. A radio channel is said to be equalised if
15 the channel impairments can be eliminated or significantly reduced.

In the field of this invention, the most conventional strategy in estimating radio channel propagation
20 conditions is to model the radio channel by a finite impulse response (FIR) filter. The channel estimation is typically performed by periodically transmitting a known data sequence, generally referred to as a training sequence, over the desired radio channel. Such training
25 sequences are a-priori known by the receiver. The training sequence is extracted from the received, desired data stream and is used to compute channel estimates.

30 In the field of this invention, namely that of Orthogonal Frequency Division Multiplexed (OFDM) systems, also termed multi-carrier systems, the data stream is divided into several (N) sub-streams. These sub-streams are transmitted on 'N' orthogonal sub-carriers at different

frequencies, for example by means of an inverse fast Fourier transform (IFFT) at the transmitting unit.

One of the main advantages of OFDM systems is their very
5 simple equalization scheme, which is reduced to a
multiplication of the FFT outputs (of each carrier
frequency) by the frequency domain channel coefficients.
Of course, the true channel coefficients are unknown, and
have to be estimated. As an illustration, the mean
10 square error between the true channel coefficients and
the channel coefficients at time 0 (time 0 being chosen
when a training symbol is received) is plotted in
function of time on FIG. 1, for an HIPERLAN/2 channel
with a mobile terminal moving at 3m/s.

15 Referring now to FIG. 2, a classical Bit interleaved and
convolutionally coded (BICC) OFDM system 200 is shown.
The BICC OFDM system 200 includes a BICC OFDM transmitter
210. The BICC transmitter 210 receives a data stream 212
20 d_i and convolutionally codes 215 the data stream to
produce an output b_i 217. The convolutionally coded
output b_i 217 is input to a bit interleaver 220. The
output from the bit interleaver 220 is then input to a
mapping function 225, which associates a subset of bits
25 x_k 228 to a location on a constellation. The type of
constellation generated by the transmitter 210 is
dependent upon the modulation scheme employed by the OFDM
modulator 230. The OFDM modulator then outputs the OFDM
modulated signal over the communication channel 235.

30 A BICC OFDM receiver 250 receives the OFDM modulated
signal over the communication channel 235. In effect,
the receiver 250 performs the inverse operations of the

BICC OFDM transmitter 210. In this regard, the receiver
250 includes an OFDM demodulator 255 to translate the
received constellation locations into a sequence of bit
subsets. The bit subsets are then input to a demapping
5 function 260. In the demapping function, bit metrics are
computed to feed the Viterbi decoder 270. This
computation involves the frequency channel coefficients,
which must be estimated periodically. A bit de-
interleaving function 265 arranges the received bit-
10 stream for decoding in the Viterbi decoder 270.

The above receiver arrangement presents a number of
significant drawbacks. In particular, the process to de-
map, decode and perform channel estimation separately, as
15 three distinct and independent functions, only enables
the respective individual operations to be optimised.

In J. Boutros, C. Lamy , F. Boixadera, "Bit-interleaved
coded modulation for multiple-input multiple-output
20 channels", IEEE ISSSTA , Sept. 2000, a method performing
joint de-mapping, decoding and channel estimation using
an estimation-maximisation (EM) algorithm and a turbo-
demodulation procedure has been proposed. However, the
proposed algorithm has been derived in a single carrier
25 context and is therefore unsuitable for OFDM
implementation.

A turbo channel estimation method using EM algorithm in
an OFDM context has been proposed in E. Jaffrot, M.
30 Siala, "Turbo channel estimation for OFDM systems on
highly time and frequency selective channels", Proc.
ICASSP2000. However, the channel estimation method
assumes, as a pre-requisite, a phase-shift keyed (PSK)
modulation scheme. As such, the method is limited in its

applications and works only for binary PSK (BPSK) and quadrature PSK (QPSK) mapping. Thus, it cannot be applied to high bit rate applications such as HIPERLAN/2 (which uses a quadrature amplitude modulation (QAM) scheme). Moreover, it uses pilot carriers, which reduces the application bit rate.

Thus, there exists a need in the field of the present invention to provide an improved channel estimation method in an OFDM communication system, wherein at least some of the aforementioned disadvantages may be alleviated.

Statement of Invention

The present invention provides a method of channel estimation and a receiver for performing channel estimation as described in the accompanying claims.

Brief Description of the Drawings

FIG. 1 illustrates a graph of mean square error (MSE) for a BRAN A channel with a mobile terminal (MT) moving at 3m/s; and

FIG. 2 shows a simplified processing block diagram of a bit-interleaved and convolutionally coded OFDM communication system.

Exemplary embodiments of the present invention will now be described, with reference to the accompanying drawings, in which:

FIG. 3 illustrates a wireless communication unit adapted in accordance with a preferred embodiment of the present invention;

- 5 FIG. 4 illustrates a channel estimation model applicable to the preferred embodiment of the present invention.

FIG. 5 illustrates a block diagram of a decoding unit adapted in accordance with a preferred embodiment of the present invention;

10

FIG. 6 illustrates two examples of mapping that can be used in the preferred embodiment of the present invention;

15

FIG. 7 illustrates a model of an OFDM system used in the preferred embodiment of the present invention;

FIG. 8 illustrates a block diagram of a decoding unit's forward-backward algorithm in accordance with a preferred embodiment of the present invention; and

20

FIG. 9 shows bit-error-rate simulation results of the channel estimator according to the preferred embodiment of the invention.

25

Description of Preferred Embodiments

In summary, the preferred embodiments of the invention described below perform blind channel estimation for each OFDM symbol, which allows the receiver to track the channel variations, and consequently to increase the time between training sequences. In particular, the channel estimate of the frequency channel coefficients for each

30

OFDM symbol is performed using an Expectation-Maximization (EM) algorithm that includes estimated channel coefficients using at least one other, and preferably all the other sub-carriers.

5

Referring now to FIG. 3, there is shown, by way of example, a block diagram of a wireless communication unit, adapted to support the inventive concepts of the preferred embodiments of the present invention. The

10 wireless communication unit 300 contains an antenna 302 preferably coupled to an antenna switch 304 that provides isolation between a receiver and a transmitter chain within the wireless communication unit 300.

15 The receiver chain shown includes receiver front-end circuitry 306 (effectively providing reception, filtering and intermediate or base-band frequency conversion). The front-end circuit 306 is serially coupled to a signal processing function 308. An output from the signal
20 processing function is provided to a suitable output device 310.

The signal processing function 308 performs all signal processing functions for the wireless communication unit
25 300, including demodulation, de-mapping, bit de-interleaving, channel estimation and decoding. In accordance with the preferred embodiments of the present invention, the signal processing unit 308 has been adapted to perform EM-based channel estimation, using
30 probabilities on coded bits. These probabilities may be provided by any channel decoding scheme yielding soft outputs, e.g. a so-called BCJR algorithm - see L. Bahl, J. Cocke, F. Jelinek and J. Raviv, "Optimal Decoding of Linear Codes for Minimizing Symbol Error Rate", IEEE

transaction on Information Theory, March 1974. The preferred embodiment uses a turbo-demodulation process, such that it is able to jointly perform de-mapping and decoding of the received signal. The signal processing
5 function 308 is further adapted inasmuch as it employs a new channel estimation method, as is further described with regard to FIG. 5.

The receiver chain shown also includes received signal
10 strength indicator (RSSI) circuitry 312 (shown coupled to the receiver front-end 306, although the RSSI circuitry 312 could be located elsewhere within the receiver chain). The RSSI circuitry is coupled to a controller 314 for maintaining overall subscriber unit control. The
15 controller 314 is also coupled to the receiver front-end circuitry 306 and the signal processing function 308 (generally realised by a digital signal processor (DSP)). The controller 314 may therefore receive bit error rate (BER) or frame error rate (FER) data from recovered
20 information. The controller 314 is coupled to the memory device 316 for storing operating regimes, such as decoding/encoding functions and the like. A timer 318 is typically coupled to the controller 314 to control the timing of operations (transmission or reception of time-
25 dependent signals) within the wireless communication unit 300.

As regards the transmit chain, this essentially includes an input device coupled in series via transmit signal
30 processor 328 to a transmitter/ modulation circuit 322. Thereafter, any transmit signal is passed through a power amplifier 324 to be radiated from the antenna 302. The transmitter/ modulation circuitry 322 and the power amplifier 324 are operationally responsive to the

controller, with an output from the power amplifier coupled to the duplex filter or circulator 304. The transmitter/ modulation circuitry 322 and receiver front-end circuitry 306 comprise frequency up-conversion and
5 frequency down-conversion functions (not shown).

Of course, the various components within the wireless communication unit 300 can be arranged in any suitable functional topology that is able to utilise the inventive
10 concepts of the present invention. Furthermore, the various components within the wireless communication unit 300 can be realised in discrete or integrated component form, with an ultimate structure therefore being merely an arbitrary selection. The preferred decoding and
15 channel estimation function can be implemented in software, firmware or hardware, with the function being implemented in a software processor (or indeed a digital signal processor (DSP)) that performs the decoding function, merely a preferred option.

20 The transmitter signal processor 328, which is shown as being distinct from the receiver signal processor 308 for clarity purposes only, includes a convolutional encoder or a turbo-coding function.

25 In accordance with a preferred embodiment of the present invention, an improved channel estimation algorithm for the OFDM system is included. The channel estimation uses an Expectation-Maximisation (EM) algorithm. This is a
30 parametric estimation algorithm, which attempts to estimate the parameters ' θ ' 404 of a system 400 from the observations of its output y 406 blindly without knowing its input x 402, as shown in the model in FIG. 4.

The EM algorithm is an iterative procedure, which maximizes the likelihood function in two steps:

- 5 (i) A first Expectation step (E-step): which comprises a computation of:

$$E_x[P(x|y, \theta^{(p)})] \quad [1]$$

and

10

- (ii) A second Maximization step (M-step):

$$\theta^{(p+1)} = \arg \max_{\theta} P(y|\theta, \hat{x}^{(p)}) \quad [2]$$

- 15 In a practical implementation, the maximisation (M-)step is performed by maximizing the auxiliary function:

$$Q(\theta, \theta^{(p)}) = E_x[\log P(x, y|\theta) | y, \theta^{(p)}] \quad [3]$$

- 20 In accordance with the preferred embodiment of the present invention, the auxiliary function of the channel estimation algorithm has been adapted to take into account OFDM specificities. Indeed, the auxiliary function has been rewritten as:

25

$$Q(H_m, H_m^{(p)}) = E_{x_m}[\log P(x_m, y_m, \tilde{H}^{(m)} | H_m) | y_m, H_m^{(p)}] \quad [4]$$

- 30 where: $\tilde{H}^{(m)}$ stands for the vector H with a 0 on the m^{th} component. This allows, when estimating the channel coefficient of the m -th sub-carrier, to use and take advantage of the prior estimations of the channel coefficients of the other frequency domain sub-carriers.

In addition, the Expectation step has been configured to be an estimation of the probability on decoded bits, which are needed for the M-step. These probabilities are
5 provided by any decoding scheme yielding soft outputs. Furthermore, the preferred embodiment of the present invention, proposes to use a turbo-demodulation procedure, in order to optimise jointly the de-mapping and the decoding steps. In this manner, the decoding
10 algorithm leads to a much better performance than a non-iterative decoding scheme.

However, it is within the contemplation of the invention that the inventive concepts herein described are
15 applicable to any convolutional encoder, i.e. it is applicable for any rate and any puncturing scheme. Furthermore, the decoding scheme of the present invention can be applied to any encoded data that can be decoded by a soft output decoder, i.e. any convolutional or turbo
20 decoder.

Referring now to FIG. 5, a block diagram model 500 of the preferred channel estimation procedure is illustrated. The received data stream 505 is demodulated in OFDM
25 demodulation function 510. The output from the demodulation function 510 is input to a channel estimation function, which incorporates an estimation function 520 and a maximization function 550.

30 The OFDM demodulated signal is input to a de-mapping function 525, which outputs de-mapped signals to a de-interleaving function 530, and thereafter to a soft output decoder function 535. In this manner, the channel

estimation function is operational over both the de-mapping and decoding functions.

5 The de-mapping function in the preferred embodiment, i.e. the function that associates a subset of bits to a modulation constellation location, is able to operate with any labelling map. For example, as shown in FIG. 6, the de-mapping operation may be performed on a subset of a 16-QAM signal, which is composed of four bits. Each
10 subset has to be associated to one of the sixteen positions of the constellation. There are a number of different ways to define the association function, which affect the performance of the decoding system. For example, constellation 610 in FIG. 6 illustrates a Gray
15 labelling structure, which is deemed optimum when a Viterbi decoder is used. However, when turbo-demodulation is used, an alternative mapping format such as the set partitioning format 620 may provide better results.

20 The output from the decoding function 535, is fed back to the de-mapping function 525 via an interleaving function 540. The output from the improved estimation function 520 is input to a maximization function 550. The output
25 from the maximization function 550 is input to the de-mapping function 525.

It is noteworthy that this arrangement also yields decoded bits, in a bit-stream 535. The bit decisions are
30 made from decision function 560. Thus, the improved channel estimation arrangement is a joint channel estimation and decoding scheme.

In accordance with the preferred embodiment of the present invention, the channel estimation operation has been adapted to take into account the OFDM specificities, using the coded bits on neighbouring frequency channels

5

Referring now to FIG. 7, a block diagram of a parallel equivalent representation of a cyclic-prefix OFDM modulator-demodulator 700 is illustrated. In effect, an OFDM transmitter wishes to emit a set of bits $\{b_n^{(m)}\}_{1 \leq m \leq M, 1 \leq n \leq N}$ 702.

10 over a channel $\{h_l\}_{1 \leq l \leq L}$ using, say, a 2^N -QAM scheme 704.

First every subset of N bits $\{b_n^{(m)}\}_{1 \leq n \leq N}$ 702 is modulated into a symbol x_m . In the OFDM context, the $\{x_m\}_{1 \leq m \leq M}$ symbols 706 are transformed from a frequency domain representation into a time domain using an inverse fast fourier transform (IFFT). The time-domain signals are then serialized and convolved by the channel filter. The signals are effectively corrupted by noise $\{n_m\}_{1 \leq m \leq M}$ 732 before they are finally returned into the frequency domain using a FFT (not shown) to produce an output signal $\{y_m\}_{1 \leq m \leq M}$ 734.

It is noteworthy that in a standard OFDM transmitted signal, the signal is confined into a spectrum mask by precluding some carriers from being used, especially the ones at the top and the bottom of the FFT. In this regard, such carrier values are set to zero.

An important characteristic of OFDM communication systems, utilised in the preferred embodiment of the present invention, is that OFDM systems are dimensioned so that the length of the channel impulse response

('CIR') is smaller than the cyclic prefix size.

Accordingly, it is possible to use the classical OFDM system model representation of FIG. 7.

5 Let us consider the case where h is a vector of M independent variables, with its first L components being L independent Rayleigh fading values with variance σ_1^2 , $l = 1, \dots, L$. Let us further assume that the $M-L$ other components are independent Rayleigh fadings with a small
10 variance ε^2 .

If the variance ε is small enough, h has been determined as providing a reasonably good model of the time domain channel. This leaves the frequency domain channel as
15 being represented by:

$$H = Fh, \text{ with } F = \frac{1}{\sqrt{M}} \left[e^{-2i\pi \frac{lk}{M}} \right]_{(l,k) \in [1,M]^2} \quad [5]$$

In accordance with the preferred embodiment of the
20 present invention, let us define a new auxiliary function that provides an improved estimate of a channel coefficient H_m . It is noteworthy that the improved channel estimate considers the channel coefficients on all other carriers in order to refine/track the primary
25 channel coefficient.

The inventors have appreciated that knowledge of the channel coefficients from other carriers is useful, as the decoder needs an estimate of the frequency channel
30 coefficients $\{H_m\}_{1 \leq m \leq M}$ to eradicate the channel effects from the received coded bits. Indeed, in the preferred embodiment of the present invention, the frequency

channel coefficients from the Fourier transform of the time channel coefficients $\{h_l\}_{1 \leq l \leq L}$ are utilised in this regard.

5 Thus:

$$\underline{H} = F \underline{h} \quad [6]$$

Where:

\underline{H} is a column vector of $\{H_m\}_{1 \leq m \leq M}$,

\underline{h} is a column vector of $\{h_l\}_{1 \leq l \leq L}$ filled with zeros
10 for the $M-L$ last coefficients, and

F is a ' $M \times M$ ' matrix filled with Fourier coefficients.

At the opposite end of the time domain, the values of
15 elements of \underline{H} , are unknown. Indeed, due to the introduction of white noise in the model, it can be readily assumed that all of the elements are corrupted.

The inventors of the present invention have appreciated
20 that a standard channel estimation method, such as

$\hat{H}_m = \frac{y_m}{x_m}$, where x_m is a known symbol, leads to a poor
result.

In contrast, the proposed method of using the knowledge
25 of the channel coefficients from other carriers helps to refine the values of channel estimate. In particular, the definition of the statistical model h and the cost function are key distinguishing features of the inventive concepts of the present invention.

30

Thus, in the auxiliary function, we add $\tilde{H}^{(m)}$ in the following manner:

$$Q(H_m, H_m^{(p)}) = E_{x_m} [\log P(x_m, y_m, \tilde{H}^{(m)} | H_m) | y_m, H_m^{(p)}] \quad [7]$$

Where:

5 $\tilde{H}^{(m)}$ stands for the vector H with a 0 on the m^{th} component.

The maximization of this function leads, after some computational effort, to the following channel estimate
10 update formula:

$$H_m^{(p+1)} = \frac{\sum_{x_m} P(y_m | x_m, H_m^{(p)}) P(x_m) [y_m \bar{x}_m - \sigma^2 (\Delta_{SH}^{-1})_m \tilde{H}^{(m)}]}{\sum_{x_m} P(y_m | x_m, H_m^{(p)}) P(x_m) \left[|x_m|^2 - \frac{\sigma^2}{v^2} + \frac{v^2}{\gamma^2} \right]} \quad [8]$$

where:

$$15 \quad \gamma^{-2} = [\Delta_{SH}^{-1}]_{(m,m)}, \quad \Delta_{SH} = SF^* \text{Diag}([\sigma_1^2 \dots \sigma_L^2 \varepsilon^2 \dots \varepsilon^2]) FS^T \quad [9]$$

and

$$v^2 = \frac{1}{M} \left[\sum_{l=1}^L \sigma_l^2 + (M-L) \varepsilon^2 \right]. \quad [10]$$

S is the information carriers selection matrix. When
20 dealing with a full sub-carrier OFDM symbol, γ^{-2} can be rewritten into:

$$\gamma^{-2} = \frac{1}{M} \sum_{l=1}^L \sigma_l^2 + \frac{M-L}{M} \varepsilon^2. \quad [11]$$

It is noteworthy that the general expression of γ^{-2} of
25 equation [9] takes into account the fact that some sub-carriers are not used, which is always the case in practice.

In practice, three parameters are needed to implement the
aforementioned formula, namely: $P(y_m | x_m, H_m^{(p)})$, $P(x_m)$ and
 $\tilde{H}^{(m)}$.

- 5 If we assume that the channel additive noise is a
Gaussian white noise of variance σ^2 , $P(y_m | x_m, H_m^{(p)})$ may be
viewed as:

$$P(y_m | x_m, H_m^{(p)}) = \frac{1}{\pi\sigma^2} e^{-\frac{|y_m - H_m^{(p)} x_m|^2}{\sigma^2}} \quad [12]$$

- 10 Where:

$P(x_m)$ is the product of the probabilities of each
coded bit involved in the symbol x_m . The turbo-
demodulation process provides an estimation of these
probabilities. Thus, $P(x_m)$ is the result of the E-step;

- 15 and

$\tilde{H}^{(m)}$ is unknown, but each of its component $\tilde{H}_i^{(m)}$ may
be taken as the current estimate of the channel
coefficient, i.e. $\tilde{H}_i^{(m)} = H_i^{(p+1)}$ for $i < m$ and $\tilde{H}_i^{(m)} = H_i^{(p)}$ for
20 $i > m$.

However, the inventors of the present invention have
recognised that the above methodology would lead to the
last set of coefficients being estimated more accurately
25 than the first set of coefficients. Hence, to remove
this drawback and improve the estimation, the inventors
propose implementing a 'forward-backward' procedure to
further improve the channel refinement.

- 30 The preferred implementation of the forward/backward
process is illustrated in FIG. 8. The channel refinement

is performed on a carrier-by-carrier basis. Received data is input to the Turbo demodulation estimation process 804, as illustrated in FIG. 6. Furthermore, the received data is also input to the maximization process 5 806, which comprises an algorithm having two steps, i.e. one 'forward' step 808 and one 'backward' step 810. The operation of the forward step 808 and the backward step 810 is performed on the received data and the channel estimation values output 812 from the estimation 10 algorithm 804. The operation of the forward step 808 and the backward step 810 is performed making bit decisions 814 using the information bit probabilities. The output of the process is a sequence of received bits 816.

15 In accordance with the preferred embodiment of the present invention, the forward step is implemented as follows:

The H_m coefficients are estimated from $m=1$ to $m=M$.

20 In this step, when computing the channel coefficient on sub-carrier m , the channel coefficient estimates on the other sub-carriers l , such that $m < l \leq M$, come from the previous iteration. The channel coefficient estimates on the other sub-carriers l such that $1('one') \leq l < m$ come from 25 the actual iteration.

The backward step is implemented as follows:

The H_m coefficients are estimated from $m=M$ to $m=1$, using the estimates of the forward step.

30

In this step, when computing the channel coefficient on sub-carrier m , the channel coefficient estimates on the other sub-carriers l such that $m < l \leq M$ come from the forward step, and the channel coefficient estimates on

the other sub-carriers l such that $1('one') \leq l < m$ come from the present backward step.

In this manner, approximately the same level of accuracy
5 of each channel coefficient can be achieved, thereby improving the channel estimate performance.

To fully evaluate the performance of this method, a set of Monte-Carlo simulations was performed over two hundred
10 channels to estimate the bit error rate (BER) and the packet error rate (PER). The simulation context was performed using one hundred OFDM symbols of sixty-four sub-carriers preceded by two pilot symbols. This is useful in obtaining a first channel estimate. The
15 simulation was performed over sixteen independent Rayleigh fading channels. A half rate convolutional encoder (035, 023) was used. Symbols were bit-interleaved with a random pattern and modulated by a 16-QAM constellation.

20 The results of the simulation are illustrated in FIG. 9 and FIG. 10. Referring now to FIG. 9, a comparison of the average BER versus signal to noise ratio (SNR) is illustrated for an OFDM system. FIG. 10 illustrates a
25 comparison of the average PER versus SNR for the OFDM system.

In both FIG. 9 and FIG. 10, the OFDM system does not refine channel estimates and performs only two iterations
30 of the turbo-demodulator per global iteration. Three curves are shown:

(i) A first curve indicates the performance without employing the inventive concepts herein before described, identified as 'NONE 2 TD';

(ii) A second curve illustrates the performance when implementing the proposed invention, identified as '1 EM-OFDM-SS 2 TD for $\epsilon^2=3e^{-3}$; and

(iii) A third curve illustrates the performance when implementing the proposed invention, identified as '1 EM-OFDM-SS2 2 TD' for $\epsilon^2=1e^{-16}$.

It is noteworthy that, by implementing the inventive concepts herein described, an improvement of around 2dB in BER/PER can be achieved. Moreover, provided that the variance ϵ parameter is small enough the setting of the parameter is not critical. Hence, the user does not have to perform precise tuning on the variance ϵ parameter.

It is within the contemplation of the invention that the aforementioned inventive concepts can be applied to any element in the communication system that performs decoding and channel estimation, for example a BTS communication unit and/or a MS.

In the preferred embodiment of the present invention, the maximization step utilises a forward-backward approach. However, it is within the contemplation of the invention that alternative maximization techniques may be used in the decoder such that the decoder is still able to benefit from the inventive concepts described herein.

It will be understood that a method of channel estimation performed by a communication unit operating in an OFDM communication system as described above, tends to provide at least some of the following advantages:

(i) A mechanism to perform jointly de-mapping, decoding and channel estimation is described, whereby their performance can be globally optimised. In particular, the modification of the EM cost function results in the modification of the channel update formula, which provides an improved decoding performance.

(ii) There is no estimation error in a noiseless case. In practice, this means that the proposed estimator performs better than the strongest-path method based estimator for high SNR conditions.

(iii) Estimation noise is partially removed from the selected channel coefficients.

(iv) There is minimal additional complexity when compared to prior art arrangements.

(v) The inclusion of OFDM specificities in a novel and inventive approach enables bit-interleaved coded modulation improvements proposed by J. Boutros et al. to be translated to an OFDM scenario. In particular, the inventive concepts can be applied to any kind of mapping, and does not use pilot carriers. Nevertheless, the inventive concepts hereinbefore described may be used in the presence of pilot carriers, if desired.

Whilst specific, and preferred, implementations of the present invention are described above, it is clear that one skilled in the art could readily apply further variations and modifications of such inventive concepts.

Thus a method of channel estimation performed by a communication unit operating in an OFDM communication

system has been provided wherein at least some of the
aforementioned disadvantages with prior art arrangements
have been alleviated.

Claims

1. A method of channel estimation in a wireless orthogonal frequency division multiplexed (OFDM) communication system (700), comprises the steps of:
 - receiving a signal in the time domain;
 - applying a Fourier transform to said received signal to obtain a frequency domain signal including a plurality of sub-carriers;
 - estimating probabilities of coded bits for at least said plurality of frequency domain sub-carriers; and
 - performing channel coefficient estimation for at least said plurality of frequency domain sub-carriers.
- 15 characterised in that
said step of performing channel coefficient estimation for each of said plurality of frequency domain sub-carriers uses channel coefficient estimates for at least one other of said plurality of frequency domain sub-carriers.
2. A method of channel estimation according to Claim 1, wherein said step of performing channel coefficient estimation for substantially each of said plurality of frequency domain sub-carriers uses channel coefficient estimation benefits from said channel coefficient estimates for substantially all the other frequency domain sub-carriers of said plurality.
- 30 3. A method of channel estimation according to Claim 2, wherein said plurality of frequency domain sub-carriers comprises substantially all the sub-carriers of said frequency domain signal.

4. A method of channel estimation according to any preceding Claim and comprising repeating said steps of estimating probabilities and performing channel
5 coefficient estimation so as to improve iteratively an accuracy of said channel coefficient estimates.

5. A method of channel estimation according to Claim 4, wherein the k th channel coefficient estimation is
10 substantially in accordance with the following equation:

$$H_k^{(p+1)} = \frac{P(y_k|x_k, H_k^{(p)}) [y_k \bar{x}_k - \sigma^2 (\Delta^{-1})_k \tilde{H}^{(k)}]}{P(y_k|x_k, H_k^{(p)}) \left[|x_k|^2 - \frac{\sigma^2}{v^2} + \frac{v^2}{\gamma^2} \right]}$$

- where $H_k^{(p+1)}$ is the $(p+1)$ th estimate and $H_k^{(p)}$ the p th estimate of the channel coefficients, y_k is the received data corresponding to the transmitted data x_k , σ^2 is the channel noise variance, $\tilde{H}^{(k)}$ is the channel coefficient
15 vector H with a 0 on the k^{th} component and Δ^{-1} , v^2 and γ^2 have the meanings indicated hereinabove.

6. A method of channel estimation according to any of Claim 4 or 5, wherein the step of performing channel
20 coefficient estimates comprises replacing previously estimated channel coefficients of said plurality of frequency domain sub-carriers with respective current channel coefficient estimates.

- 25 7. A method of channel estimation according to any of Claims 4 to 6, wherein repeating said step of performing channel coefficient estimation comprises applying a cost function on an Expectation-Maximization algorithm on said plurality of frequency domain sub-
30 carriers to improve said channel coefficient estimates.

8. A method of channel estimation according to Claim 7, wherein said step of performing a channel coefficient estimation includes calculating an auxiliary function, the method further characterised by the step of:

5 performing a Maximisation process on said auxiliary function in substantially the following manner:

$$Q(H_m, H_m^{(p)}) = E_{x_m} [\log P(x_m, y_m, \tilde{H}^{(m)} | H_m) | y_m, H_m^{(p)}].$$

9. A method of channel estimation according to any
10 of Claims 4 to 8, wherein said step of performing a channel coefficient estimation includes applying a forward-backward algorithm on said received signal to said plurality of channel coefficient estimates in which estimates are made in a first order of said plurality of
15 frequency domain sub-carriers and subsequently estimates are made in a reversed order of said plurality of frequency domain sub-carriers so as substantially to equalise an estimation accuracy across said plurality of frequency domain sub-carriers.

20

10. A method of channel estimation according to any preceding Claim, wherein said step of channel estimation is performed on received data that is decoded by a soft output decoder, said decoder providing estimations of
25 said probabilities.

11. An orthogonal frequency division multiplexed (OFDM) receiver for a method of channel estimation as claimed in any preceding Claim, and comprising:

30 demodulation means for applying said Fourier transform to said received signal to obtain said frequency domain signal including a plurality of sub-carriers;

decoding means for decoding the received signal
and estimating said probabilities of coded bits for at
least said plurality of frequency domain sub-carriers;
and

- 5 channel estimation means for performing channel
coefficient estimation for each of said plurality of
frequency domain sub-carriers using channel coefficient
estimates for at least one other of said plurality of
frequency domain sub-carriers.

10

Abstract

COMMUNICATION UNIT AND METHOD OF CHANNEL ESTIMATION IN AN OFDM COMMUNICATION SYSTEM

5 A method of channel estimation in a wireless orthogonal
frequency division multiplexed (OFDM) communication
system (700). The method comprises the steps of
receiving a frequency signal and applying a fast fourier
10 transform (FFT) to the received frequency signal to
obtain a plurality of frequency domain sub-carriers.
Probabilities on coded bits are produced for a number of
the plurality of frequency domain sub-carriers and
channel coefficient estimation is performed for each of
15 the plurality of frequency domain sub-carriers using
channel coefficient estimates of other ones (preferably
all others) of the plurality of frequency domain sub-
carriers, which are based on the probabilities on coded
bits. An OFDM communication unit and OFDM communication
20 system are also provided.

This provides at least the advantage that the OFDM
receiver is able to perform jointly de-mapping, decoding
and channel estimation. This enables their respective
25 performances to be globally optimised. In particular,
the modification of an expectation-maximisation cost
function results in the modification of the channel
update formula, which provides an improved decoding
performance

30 {FIG. 5 to accompany abstract}

FIG. 1

100





FIG. 2
Prior Art

FIG. 3




FIG. 4




FIG. 5






FIG. 6



Example: Gray labelling



5 Example: Set-Partitioning labelling







FIG. 9

900\



PCT Application
PCT/EP2003/050774



This Page is inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☒ FADED TEXT OR DRAWING
- ☐ BLURED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☒ COLORED OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REPERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images
problems checked, please do not report the
problems to the IFW Image Problem Mailbox**